	PIG V	Vire & Cable	k Cable		ination Instruction	s T-11117
	A Division of the Angelus Corporation Ph (262)-246-0500 Fax (262) 246-0450 www.picwire.com W220 N1051 Springdale Road, Waukesha, WI 53186			Approved : PFT Distribution : USER		Date : 03/11/21
						Rev 0 Uncontrolled if Printed
	Termination	Instructions for PIC F (for E6A0824, E6A28	P/ <b>N 111170 - RJ45 F</b> 24, E6A3824, & E6A68	· ·		LIEF
	Required Tooling : Recommended Hand Tools :	PIC P/N 111183 Crimp To X-acto Knife, Sharp Razon	T-1 II4 Ch :-14	M:fi C11 C:-1-	Saine	
	Install Labels (if applicable), then	install the 1" long piece of i	12/3 ATUM. Make			nches - Not to Scale .900"
	tut A @ 0.900" from end of cable, through jacket only. DO NOT nick or cut into the raids. Remove the jacket (Fig. 1).					
)	Flair and fold braid back over the	jacket (Fig. 2).				
)	Remove the foil shield and PTFE tape at Cut A to expose the twisted pairs. Move wires o the side and carefully trim spline flush with Cut A (Fig. 3); verify insulation integrity.				Figure 2	
)	Untwist each pair, for approximately half of the stripped length, carefully straighten each wire. Align wires into desired wire configuration per work print, and install wires into the load bar. Use installed load bar to "comb" or work the wires into shape, until thoroughly straight for approximately half the cut length, while maintaining pairs' twist close to Cut A. Set far edge of load bar at .830" from jacket and trim conductors flush (Fig. 4).					
	Set far edge of load bar at .830" f	rom jacket and trim conduc	tors flush (Fig. 4).		Figure 3	trim spline
)	Bend the connector strain relief tab down, to allow entry for wires. Install wires into the connector body, keeping alignment intact. To complete full insertion, push while lightly wiggling the cable to help the conductors slide into their channels. Proper insertion is indicated by viewing ALL of the wire conductors through the front end of the connector body. Use Magnifier if needed (Fig. 5).					
					Figure 4 maintain t	wist trim wire flu
)	Smooth the braid down over the jacket. Bend the strain relief tab to align with the cable, careful to keep the braid strands enclosed (Fig. 6). Lightly bend the ends of the strain relief tabs in to prep for crimping.					
)	Verify full insertion before crimpi crimp tool. Trim any braids past th					.830"
6)	Bring the ATUM $12/3 \times 1.0$ " over the shoulder of the connector, and shrink onto the connector and cable (Fig. 8), while taking care to shield the RJ45 latching tab from excessive heat. Verify full travel of the latching tab, trim back shrink tube if it impedes the latching tab (Fig. 9).				Figure 5 Conductor	rs should be visible and fully inserte
	Figure 6 braid strands fully enclosed.	Figure 7	trim excess braids		Figure 8 shrink 12/	3 ATUM over shoulder
	RJ45 Wiring Configuration for 568A or 568B				White / Orange	
				2 Green 3 White / Orange 4 Blue 5 White / Blue	Orange White / Green Blue White / Blue	
		V	Top View	5 White / Blue 6 Orange 7 White / Brown 8 Brown	Green White / Brown Brown	